

SANYO

No.2898

LA7323, 7323M

Monolithic Linear IC

Single-Chip
HQ Luminance Signal Processor

The LA7323,7323M are single-chip HQ (High Quality) VTR luminance signal processor ICs that contain a detail enhancer, a line noise canceler, etc. The LA7323,7323M can be used in conjunction with preamp/recording amp ICs LA7320 (2-head use) or LA7321 (4-head use) to perform all the functions of luminance signal processing.

Features

- Very streamlined ICs that are placed in very small-sized packages (LA7323:DIP30S, LA7323M:MFP30S) and use a minimum number of external parts. (There are no other ICs of this type that use less external parts than those the LA7323,7323M use.)
- Adjustment-free E/E level, white/dark clip level
- On-chip 75Ω video driver
- On-chip edit control function
- The video AGC range is so wide and satisfactory as to be suitable for copy guard.
- Excellent picture stability at the special PB mode because of on-chip PB dark clip circuit

Functions**REC section**

Video AGC, detail enhancer, nonlinear preemphasis, main preemphasis, white clip, dark clip, FM modulation $1/2f_H$ carrier shift

PB section


FM AGC, dropout compensation (base band), double limiter, FM demodulation, dynamic de-emphasis, line noise canceler, noise canceler, sync expansion, Y/C mix, muting, pseudo V insertion, pseudo H insertion, white peak clip, picture control, PB dark clip

REC/PB


Sync separation, sync chip clamp, feedback clamp, video amp, 75Ω video driver

Note) The specifications for the LA7323M are not final. When ordering the LA7323M, check the delivery specification.

Case Outline 3061-D30SIC [LA7323]
(unit: mm)



Case Outline 3073A-M30IC [LA7323M]
(unit: mm)



Specifications and information herein are subject to change without notice.

SANYO Electric Co., Ltd. Semiconductor Overseas Marketing Div.
Natsume Bldg., 18-6, 2-chome, Yushima, Bunkyo-ku, TOKYO 113 JAPAN

N228TA.TS No.2898-1/13

LA7323,7323M

Maximum Ratings at $T_a = 25^\circ\text{C}$

Maximum Supply Voltage	V_{CC} max	7.0	V
Allowable Power Dissipation	P_d max $T_a = 65^\circ\text{C}$	600	mW
Operating Temperature	T_{opg}	-10 to +65	$^\circ\text{C}$
Storage Temperature	T_{stg}	-40 to +125	$^\circ\text{C}$

Operating Conditions at $T_a = 25^\circ\text{C}$

Supply Voltage	V_{CC}	5.0	V
Operating Voltage Range	V_{CC} op	4.8 to 5.5	V

Operating Characteristics at $T_a = 25^\circ\text{C}$, $V_{CC} = 5.0\text{V}$

No.	Characteristic	Symbol	Test Conditions		min	typ	max	unit	
			Input	Output					
	(REC Mode)								
1	Current Dissipation REC	I _{CCR}	T22		P _{in} 22 flow-in current at V _{CC} : 5.0V	50	65	80	mA
2	AGC Control	C _{AGC}	T24	T6	V _i : 1.0Vp-p video (0dB) Adjust VR2 so that output 0.5 Vp-p is obtained.				
3	AGC Control Voltage	V _{AGC}	T24	T19	V _i : 1.0Vp-p video, output DC level	4.3	4.5	4.7	V
4	AGC Detection Voltage	V _{AD}	T24	T27	V _i : 1.0Vp-p video, output DC level	1.3	1.45	1.6	V
5	EE Output Level-1	V _{EE1}	T24	T21A	V _i : 1.0Vp-p video, output level	0.95	1.00	1.05	Vp-p
6	EE Output Level-2	V _{EE2}	T24	T21A	V _i : 4.0Vp-p video, output level	1.00	1.15	1.30	Vp-p
7	AGC Control Characteristic-1	AGC1	T24	T7	(+12dB) V _i : 4.0Vp-p video, output level	1.07	1.17	1.27	Vp-p
8	AGC Control Characteristic-2	AGC2	T24	T7	(+6dB) V _i : 2.0Vp-p video, output level	1.01	1.05	1.07	Vp-p
9	AGC Control Characteristic-3	AGC3	T24	T7	(−6dB) V _i : 0.5Vp-p video, output level	0.93	0.95	0.99	Vp-p
10	AGC Control Characteristic-4	AGC4	T24	T7	V _i : 0.7Vp-p lumi (+12dB sync) V _i : 1.2Vp-p sync sync level	280	350	420	mV pp
11	AGC Control Characteristic-5	AGC5	T24	T7	V _i : 0.7Vp-p lumi (+6dB sync) V _i : 0.6Vp-p sync sync level	240	310	380	mV pp
12	AGC Control Characteristic-6	AGC6	T24	T7	V _i : 0.7Vp-p lumi (−6dB sync) V _i : 0.15Vp-p sync sync level	150	200	250	mV p-p

Note) The AGC characteristics must meet the copy guard test tape (VAG-1) requirements. (AGC level 40% or less)

Continued on next page.

Continued from preceding page.

No.	Characteristic	Symbol	Test Conditions		min	typ	max	unit	
			Input	Output					
	(REC Mode)								
13	Sync Separation Output Level	V _{SY}	T24	T17	V _i : 1.0V _{p-p} video, output pulse peak	3.5	3.8	4.4	V _{p-p}
14	Sync Separation Pulse Width	P _{WSY}	T24	T17	V _i : 1.0V _{p-p} video, output pulse width	4.0	4.3	4.6	μs
15	Sync Separation Leading Edge Delay Time	Δt _{ey}	T24	T17	V _i : 1.0V _{p-p} video	1.0	1.4	1.8	μs
16	Sync Separation Threshold Level	T _{HSY}	T24	T17	Input level 1.0V _{p-p} : 0dB when input level is attenuated and output pulse width becomes wider than sync separation pulse width by 1μs.	-16	-14		dB
17	Preamphasis Voltage Gain	G _{PE}	T6A	T2	V _i : 500mV _{p-p} (0dB) f: 10kHz	-1.0	0	0.5	dB
18	Detail Enhancer Response Characteristic-1	G _{DE1}	T6A	T2	V _i : 500mV _{p-p} (0dB) f: 2MHz G _{PE} : 0dB	0	0.15	0.5	dB
19	Detail Enhancer Response Characteristic-2	G _{DE2}	T6A	T2	V _i : 158mV _{p-p} (-10dB) f: 2MHz G _{PE} : 0dB	0.3	0.6	0.9	dB
20	Detail Enhancer Response Characteristic-3	G _{DE3}	T6A	T2	V _i : 50mV _{p-p} (-20dB) f: 2MHz G _{PE} : 0dB	1.3	1.9	2.5	dB
21	Detail Enhancer Response Characteristic-4	G _{DE4}	T6A	T2	V _i : 15.8mV _{p-p} (-30dB) f: 2MHz G _{PE} : 0dB	1.9	2.5	3.1	dB
22	Detail Enhancer Response Characteristic-5	G _{DE5}	T6A	T2	V _i : 5mV _{p-p} (-40dB) f: 2MHz G _{PE} : 0dB	1.9	2.7	3.5	dB
23	Nonlinear Emphasis Response Characteristic-1	G _{NE1}	T6A	T2	V _i : 500mV _{p-p} (0dB) f: 2MHz G _{PE} : 0dB	0.5	1.4	2.3	dB
24	Nonlinear Emphasis Response Characteristic-2	G _{NE2}	T6A	T2	V _i : 158mV _{p-p} (-10dB) f: 2MHz G _{PE} : 0dB	2.6	3.8	5.2	dB
25	Nonlinear Emphasis Response Characteristic-3	G _{NE3}	T6A	T2	V _i : 50mV _{p-p} (-20dB) f: 2MHz G _{PE} : 0dB	4.9	6.4	7.9	dB
26	Nonlinear Emphasis Response Characteristic-4	G _{NE4}	T6A	T2	V _i : 15.8mV _{p-p} (-30dB) f: 200kHz G _{PE} : 0dB	0.7	1.4	2.1	dB
27	Main Emphasis Response Characteristic-1	G _{ME1}	T6A	T2	V _i : 50mV _{p-p} (-20dB) f: 200kHz G _{PE} : 0dB	4.9	5.2	5.5	dB
28	Main Emphasis Response Characteristic-2	G _{ME2}	T6A	T2	V _i : 50mV _{p-p} (-20dB) f: 2MHz G _{PE} : 0dB	13.1	13.6	14.1	dB
29	White Clip Level	L _{WC}	T6A	T2	V _i : 0.5V _{p-p} video	187	195	203	%
30	Dark Clip Level	L _{DC}	T6A	T2	V _i : 0.5V _{p-p} video	-48	-55	-62	%

Continued on next page.

Continued from preceding page.

No.	Characteristic	Symbol	Test Conditions		min	typ	max	unit	
			Input	Output					
	(REC Mode)								
31	FM Modulator Output Level	V _{FM}	—	T30	Output level when output frequency is set to 4MHz with VR1 at no load mode	1.3	1.5	1.7	V _{p-p}
32	FM Modulator 2nd Distortion	H _{MOD}	T6	T30	8MHz component / 4MHz component ratio obtained in above-mentioned state		-40	-35	dB
33	FM Modulator Modulation Sensitivity	S _{MOD}	T6	T30	Output frequency change 2×(f _{4.0} - f _{3.5}) when DC 3.5V, 4.5V are applied to pin 6	1.6	2.0	2.4	MHz
34	FM Modulator Linearity	L _{MOD}	T6	T30	Output frequency when 3.75V DC is applied to pin 6 : f _{3.75} $L_{MOD} = \frac{f_{3.75} - (f_{4.0} + f_{3.5}) / 2}{S_{MOD}} \times 100$	3.0	0	3.0	%
35	EP 1/2 Carrier Shift-1	C _{S1}	T6	T2	Output frequency change at SW12 : 1 SW13 : 1→2	6.0	7.5	9.0	kHz
	(PB Mode)								
1	Current Dissipation	I _{CCP}	T22		Pin 22 flow-in current at V _{CC} : 5.0V	65	80	95	mA
2	FM AGC Detection Voltage-1	V _{FD1}	T26	T27	V _i : 200mV _{p-p} (0dB) f : 4MHz	0.80	0.90	1.00	V
3	FM AGC Detection Voltage-2	V _{FD2}	T26	T27	V _i : 400mV _{p-p} (+6dB) f : 4MHz	1.05	1.15	1.25	V
4	FM AGC Detection Voltage-3	V _{FD3}	T26	T27	V _i : 50mV _{p-p} (-12dB) f : 4MHz	0.69	0.69	0.79	V
5	Dropout Detection Level	I _{DOC1}	T26	T28	Input level when T28 Low→High is caused by input f : 4MHz High→Low	4.0	5.0	6.0	mV _{pp}
6	Dropout Reset Level	I _{DOC2}	T26	T28	Input level when T28 High→Low is caused by input f : 4MHz High→Low	4.8	6.0	7.2	mV _{pp}
7	Dropout Detection Pulse Output Level	V _{DOC}	—	T28	Output DC level at no input mode	3.5	3.9	4.4	V _{p-p}
8	FM Demodulation Voltage-1	V _{DEM4} (1)	T26	T7A	V _i : 200mV _{p-p} (0dB) f : 4MHz output voltage	1.1	1.30	1.5	V
9	FM Demodulation Voltage-2	V _{DEM4} (2)	T26	T7A	V _i : 400mV _{p-p} (+6dB) f : 4MHz output voltage	1.1	1.30	1.5	V
10	FM Demodulation Voltage-3	V _{DEM4} (3)	T26	T7A	V _i : 50mV _{p-p} (-12dB) f : 4MHz output voltage	1.1	1.30	1.5	V

Continued on next page.

Continued from preceding page.

No.	Characteristic	Symbol	Test Conditions		min	typ	max	unit	
			Input	Output					
	(PB Mode)								
11	FM Demodulation Sensitivity-1	$S_{DEM(1)}$	T26	T7A	V_i : 200mVp-p, f: 2MHz output voltage $V_{DEM2(1)}$ V_i : 200mVp-p, f: 6MHz output voltage $V_{DEM6(1)}$ Calculate using $S_{DEM(1)} = (V_{DEM2(1)} - V_{DEM6(1)}) / 4$	0.16	0.20	0.24	V/ MHz
12	FM Demodulation Sensitivity-2	$S_{DEM(2)}$	T26	T7A	V_i : 400mVp-p, f: 2MHz output voltage $V_{DEM2(2)}$ V_i : 400mVp-p, f: 6MHz output voltage $V_{DEM6(2)}$ Calculate using $S_{DEM(2)} = (V_{DEM2(2)} - V_{DEM6(2)}) / 4$	0.16	0.20	0.24	V/ MHz
13	FM Demodulation Sensitivity-3	$S_{DEM(3)}$	T26	T7A	V_i : 50mVp-p, f: 2MHz output voltage $V_{DEM2(3)}$ V_i : 50mVp-p, f: 6MHz output voltage $V_{DEM6(3)}$ Calculate using $S_{DEM(3)} = (V_{DEM2(3)} - V_{DEM6(3)}) / 4$	0.16	0.20	0.24	V/ MHz
14	FM Demodulation Linearity-1	$L_{DEM(1)}$	—	—	$L_{DEM(1)} = \frac{V_{DEM4(1)} - (V_{DEM2(1)} + V_{DEM6(2)}) / 2}{V_{DEM2(1)} - V_{DEM6(1)}} \times 100$	-3.5	0	3.5	%
15	FM Demodulation Linearity-2	$L_{DEM(2)}$	—	—	$L_{DEM(1)} = \frac{V_{DEM4(1)} - (V_{DEM2(1)} + V_{DEM6(2)}) / 2}{V_{DEM2(2)} - V_{DEM6(2)}} \times 100$	-3.5	0	3.5	%
16	FM Demodulation Linearity-3	$L_{DEM(3)}$	—	—	$L_{DEM(1)} = \frac{V_{DEM4(1)} - (V_{DEM2(1)} + V_{DEM6(2)}) / 2}{V_{DEM2(3)} - V_{DEM6(3)}} \times 100$	-3.5	0	3.5	%
17	Carrier Leak-1	$C_L(1)$	T26	T7	V_i : 200mVp-p, f: 4MHz Output frequency 4MHz component / 8MHz component ratio		-40	-35	dB
18	Carrier Leak-2	$C_L(2)$	T26	T7	V_i : 400mVp-p, f: 4MHz Output frequency 4MHz component / 8MHz component ratio		-40	-35	dB
19	Carrier Leak-3	$C_L(3)$	T26	T7	V_i : 50mVp-p, f: 4MHz Output frequency 4MHz component / 8MHz component ratio		-40	-35	dB

Continued on next page.

Continued from preceding page.

No.	Characteristic	Symbol	Test Conditions		min	typ	max	unit	
			Input	Output					
	(PB Mode)								
20	PB Output Level (Through Gain)	V_{PB}	T9.10	T21A	V_i : 300mVp-p (0dB) f : 10kHz	4.8	5.8	6.8	dB
21	PB Output Frequency Characteristic	F_{PB}	T9.10	T21A	V_i : 300mVp-p, f : 3MHz Output level / V_{PB} (10kHz)	-0.6	-0.3	0	dB
22	Noise Limiter Level	N_{LIM}	T10	T21A	V_i : 100mVp-p f : 100kHz	45	60	72	mV pp
23	Noncorrelation Detection Level	L_H		T11	T10: 3.9V, T9: 3.9V, ΔV when voltage only applied to T9 is increased and T11 output level is changed from Low to High	65	80	95	mV
24	Noncorrelation Detection Pulse Output Level	V_H		T11	Output level when above mentioned T11 output is at High	3.5	3.8	4.4	Vp-p
25	De-emphasis Response Characteristic-2	G_{D2}	T9.10	T21A	V_i : 158mVp-p (-10dB) f : 2MHz V_{PB} : 0dB	-3.1	-2.2	-1.3	dB
26	De-emphasis Response Characteristic-3	G_{D3}	T9.10	T21A	V_i : 50mVp-p (-20dB) f : 2MHz V_{PB} : 0dB	-4.7	-3.8	-2.9	dB
27	De-emphasis Response Characteristic-4	G_{D4}	T9.10	T21A	V_i : 158mVp-p (-10dB) f : 200kHz V_{PB} : 0dB	-1.2	-0.7	-0.2	dB
28	HP-noise Canceler Response Characteristic-1	G_{N1}	T9.10	T21A	V_i : 158mVp-p (-10dB) f : 1MHz V_{PB} : 0dB	-1.7	-1.2	-0.7	dB
29	HP-noise Canceler Response Characteristic-2	G_{N2}	T9.10	T21A	V_i : 50mVp-p (-20dB) f : 1MHz V_{PB} : 0dB	-4.3	-3.3	-2.3	dB
30	HP-noise Canceler Response Characteristic-3	G_{N3}	T9.10	T21A	V_i : 15.8mVp-p (-30dB) f : 1MHz V_{PB} : 0dB	-10.0	-8.5	-7.0	dB
31	PIC-cont Hardware Response Characteristic-1	G_{PH1}	T9.10	T21A	V_i : 150mVp-p f : 1MHz V_{PB} : 0dB	2.7	3.7	4.7	dB
32	PIC-cont Hardware Response Characteristic-2	G_{PH2}	T9.10	T21A	V_i : 150mVp-p f : 2MHz V_{PB} : 0dB	4.9	5.9	6.9	dB
33	PIC-cont Software Response Characteristic-1	G_{PS1}	T9.10	T21A	V_i : 150mVp-p f : 1MHz V_{PB} : 0dB	-4.0	-3.0	-2.0	dB
34	PIC-cont Software Response Characteristic-2	G_{PS2}	T9.10	T21A	V_i : 150mVp-p f : 2MHz V_{PB} : 0dB	-7.6	-6.6	-5.6	dB
35	Chroma Amp Voltage Gain	G_C	T19A	T21	V_i : 100mVp-p f : 3MHz	11.0	12.0	13.0	dB


Continued on next page.

Continued from preceding page.







No.	Characteristic	Symbol	Test Conditions		min	typ	max	unit	
			Input	Output					
	(PB Mode)								
36	Chroma Amp Frequency Characteristic	F_C	T19A	T21	V_i : 100mVp-p, f: 4MHz, output level / G_C (3MHz) output ratio	-0.5	0	dB	
37	Sync Expansion Ratio	L_{SYNC}	T9.10	T21	V_i : 0.5Vp-p video (lumi: 0.35, sync: 0.15) Sync / output peak ratio	30.0	31.5	33.0	%
38	Pseudo V Insertion Level	L_{VD}	T9.10	T21	V_i : 0.5Vp-p video Output DC difference between output sync chip potential at S11: 1 and output sync chip potential at S11: 3	-80	0	+80	mV
39	Pseudo H Insertion Level	L_{HD}	T9.10	T21	V_i : 0.5Vp-p video Output DC difference between output pedestal potential at S11: 1 and output pedestal potential at S11: 2	0	75	150	mV
40	PB Peak Clip Level	P_C	T9.10	T21	V_i : 0.75Vp-p video Output peak	2.4	2.5	2.6	Vp-p
41	DS Amp Voltage Gain	G_{DS}	T9	T12	V_i : 500mVp-p f: 10kHz	-0.5	0	0.5	dB

DISCONTINUED

LA7323,7323M Block Diagram









Pin Description

Pin No.	Pin Function	Interface	Typical DC	Remarks
1	FM MOD-IN		$\frac{2.4}{(3.4)}$	
2	PRE-MEPH OUT		$\frac{2.4}{(2.5)}$	
3	MAIN-EMPH FEEDBACK IN		$\frac{2.4}{(2.2)}$	
4	NL-EMPH FIL DOC STOP		$\frac{2.95}{(2.75)}$	
5	DETAIL-FIL PB-H		$\frac{2.55}{}$	
6	REC CLAMP IN		$\frac{3.2}{}$	
7	REC AGC OUT PB DEMOD OUT		$\frac{V_{sync}}{2.35}$	
8	GND			







Continued on next page.

Continued from preceding page.

Pin No.	Pin Function	Interface	Typical DO	Remarks
9	PB CLAMP-IN		3.2	
10	YD CLAMP-IN		3.2 3.2	
11	CORR DET. OUT			
12	CCD DRIVE		2.75 2.75	
13	N.L. DE-EMPHA FIL		(4.5) 2.8	
14	NOICAN FIL - 1		(4.5) 2.8	
15	NOICAN FIL - 2		(4.5) 4.15	

Continued on next page.

Continued from preceding page.

Pin No.	Pin Function	Interface	Typical DC	Remarks
16	SYNC SEP FIL		$\frac{3.5}{3.5}$	
17	H-SYNC-OUT			
18	PIC-CONT			
19	PB CHROMA IN		$\frac{3.7}{3.7}$	
20	MUTE DUMMY-V DUMMY-H			
21	VIDEO-OUT			
22	Vcc			
23	F.B.C-FIL		$\frac{3.2}{3.2}$	

Continued on next page.

Continued from preceding page.

Pin No.	Pin Function	Interface	Typical DC	Remarks
24	VIDEO-IN		$\frac{3.3}{3.3}$	
25	AGC-FIL-1		$\frac{3.1}{(4.0)}$	
26	PB-FM-IN		$\frac{(3.6)}{3.7}$	
27	AGC-FIL-2		$\frac{1.4}{0.9}$	
28	DOC DET OUT			
29	SP-H SW-30			
30	REC-FM OUT			

The application circuit diagrams and circuit constants herein are included as an example and provide no guarantee for designing equipment to be mass-produced.
The information herein is believed to be accurate and reliable. However, no responsibility is assumed by SANYO for its use; nor for any infringements of patents or other rights of third parties which may result from its use.